


Celesco's model RT8101 provides a voltage feedback signal for rotational position. The sensing element of this device is a precision plastic-hybrid potentiometer which provides superb linearity and resolution.

The RT8101 provides extended rotational position feedback from as little as 1/8 of a turn f.s. all the way up to 200 turns f.s. Because the sensor is potentiometric, the RT8101 is absolute and will maintain position information even after a loss of power.

Output Signal



*—1K, 5K , 10K-ohm and bridge circuit also available. see ordering info.

RT8101

0-45° to 0-200 Turns • Voltage Divider

Industrial Grade Rotational Position Sensor

Absolute Rotary Position up to 200 turns

Aluminum or Stainless Steel Enclosure Options

IP68 / NEMA 6

General

Full Stroke Range 0-0.125 to 0-200 turns

Output Signal Options voltage divider (potentiometer)

Accuracy 0.15% to 1.25%, see ordering information

Repeatability $\pm 0.05\%$ full stroke Resolution essentially infinite

Enclosure Material Options powder-painted aluminum or stainless steel

Sensor plastic-hybrid precision potentiometer

Potentiometer Cycle Life see ordering information

Shaft Loading up to 10 lbs. radial and 5 lbs. axial

Starting Torque (25°C) 2.0 in-oz., max.

Weight, Aluminum (Stainless 3 lbs. (6 lbs.) max.

Steel) Enclosure

Electrical

Input Resistance Options see ordering information

Power Rating, Watt 2.0 at 70°F derated to 0 at 250°

Recommended Maximum Input 30 V (AC/DC)

Voltage

Output Signal Change Over Full 94% ±4% of input voltage

Stroke Range

Environmental


Enclosure NEMA 4/4X/6, IP 67/68


Operating Temperature -40° to 200°F (-40° to 90°C)

Vibration up to 10 g to 2000 Hz maximum

SENSOR SOLUTIONS /// RT8101 12//2015 Page 1

Outline Drawing






mounting holes: for .25 in. shaft option, mounting holes are threaded #10-32 x 0.375 deep 120° apart on a 2.00 inch dia. BC

for 6mm shaft option, mounting holes are threaded M6 x 9 mm deep 120° apart on a 50,8 mm dia. BC

reference mark: full counter-clockwise position - align mark on shaft to mark on face for start of measurement range



DIMENSIONS ARE IN INCHES [MM] tolerances are ± 0.02 in. [± 0.5 mm] unless otherwise noted

Ordering Information

Model Number:

Sample Model Number:

RT8101 - 0005 - 111 - 1110

nange: a enclosure:

shaft diameter:

mounting style: output signal: electrical connection: 5 turns (clockwise shaft rotations) aluminum

.25 inches face mount 500 ohm potentiometer 6-pin plastic connector

Full Stroke Range:

order code:	R125	0R25	0R50	0001	0002	0003		0005	0010	0020
clockwise shaft rotations, min:	0.125	0.25	0.50	1	2	3		5	10	20
accuracy (% of f.s.):	1.25%	1.25%	0.5%	0.5%	0.5%	0.2%		0.2%	0.15%	0.15%
potentiometer cycle life*:	2.5×10^{6}	2.5 x 10 ⁶	5 x 10 ⁵	- 1	5 x 10 ⁵	2.5 x 10 ⁵	2.5 x 10 ⁵			


order code:	0030	0040	0050	0800	0100	0120	0140	0180	0200
clockwise shaft rotations, min:	30	40	50	80	100	120	140	180	200
accuracy (% of f.s.):	0.15%	0.15%	0.15%	0.15%	0.15%	0.15%	0.15%	0.15%	0.15%
potentiometer cycle life*:	2.5×10^{5}	2.5 x 10 ⁵	2.5×10^5						

*–number of times the sensor shaft can be cycled back and forth from beginning to end and back to the beginning before any measurable signal degradation may occur.


Enclosure Material:




Shaft Diameter:




Mounting Style:



Output Signals:





Notes: $\left\{ \begin{array}{ll} * & - \text{Test pressure: } 100 \text{ feet } [30 \text{ meters}] \text{ } H_2O \text{ } (40 \text{ PSID}); \text{ Test Medium: Air; Duration: } 2 \text{ hours.} \\ ** & - \text{NEMA } 4\text{X applies to stainless steel enclosure only.} \end{array} \right.$

NORTH AMERICA

Measurement Specialties, Inc., a TE Connectivity company 20630 Plummer Street Chatsworth, CA 91311 Tel +1 800 423 5483 Tel +1 818 701 2750

Fax +1 818 701 2799 info@celesco.com

TE.com/sensorsolutions

Measurement Specialties, Inc., a TE Connectivity company.

Measurement Specialties, TE Connectivity, TE Connectivity (logo) and EVERY CONNECTION COUNTS are trademarks. All other logos, products and/or company names referred to herein might be trademarks of their respective owners.

The information given herein, including drawings, illustrations and schematics which are intended for illustration purposes only, is believed to be reliable. However, TE Connectivity makes no warranties as to its accuracy or completeness and disclaims any liability in connection with its use. TE Connectivity's obligations shall only be as set forth in TE Connectivity's Standard Terms and Conditions of Sale for this product and in no case will TE Connectivity be liable for any incidental, indirect or consequential damages arising out of the sale, resale, use or misuse of the product. Users of TE Connectivity products should make their own evaluation to determine the suitability of each such product for the specific application.

© 2015 TE Connectivity Ltd. family of companies All Rights Reserved.

RT8101 12/01/2015